french
publish

Note: Attention: Work in progress - page under construction

# UHSDR development - Build using eclipse

## Preconditions, Assumptions, Scope

- UHSDR toolchain installed, see here

## Pull UHSDR source from Github, import into eclipse

- Goto https://github.com/df8oe/UHSDR and click button “clone or download”
- Unpack the downloaded .zip file on your hard disk. Do not change the name, do not change the internal zip structure
- In Eclipse, choose “File→Import”.
- .. then choose “General→Existing Projects into Workspace”.
- Then choose the folder “mchf-eclipse in the path where you just downloaded the zip file as “root-directory”
- The project is now recognized and can be imported

## Build UHSDR using eclipse

- Project → Build Configurations → Set Active → DebugLibOVI40 (OVI49 DSP Library (STM32F7))
- Click on the “hammer” in the tool bar
- Watch Console window in Eclipse - if all ok console output ends with ” … Build finished …“

- Project → Build Configurations → Set Active → DebugOVI40 (OVI40 Firmware (STM32F7) …)
- Click on the “hammer” in the tool bar
- Watch Console window in Eclipse - if all ok console output ends with ” … Build finished …“

Newly built binary fw-ovi40.bin can be found in the eclipse project explorer (left sidebar): mchf-eclipse → DebugOVI40 → fw-ovi40.bin

## Download new firmware .bin to OVI40 UI

- Please refer to https://www.amateurfunk-sulingen.de/wiki/doku.php?id=en:uhsdr:uhsdrfw#st-link_v2_firmware_upgrade
- UHSDR FW build should run.
- Hit switch “Menu”, then select “System Info” and “Build”. Check the build date and time

corresponds to your compile time in eclipse approximatelly

## Generate .dfu file from .bin file

With .bin file the FW can be installed via USB stick of ST-Link/V2 adapter. You may want to create a dfu file from the bin file so that the DfuSE FW install method can be used.

Section 4.2.1 of STM manual UM0412 describes step-by-step the generation of a .dfu file.

The ST-Micro UM0412 manual on DfuSe can be found

here

. Original source is this.

## Eclipse user guide

- User guide can be found here.
- Profiling is described here

This covers basic usage as well as advanced tools such as profiling and others.

## Debug, tracing, real-time diagnostics

- nice summary of Cortex M tools here
- OpenOCD & Eclipse debug step-by-step instructions
- AN4989 Application note STM32 microcontroller debug toolbox
- Concurrent use of ST-Link debugger and SWO Viewer not possible, see here - but this link states Eclipse support in debugger for SWO?
- J-Link Debug Probe here

## Further reading

- https://www.amateurfunk-sulingen.de/forum/index.php?board=15;action=display;threadid=313;start=0
- https://www.amateurfunk-sulingen.de/forum/index.php?board=15;action=display;threadid=263
- SWV and SWO and Eclipse explaind here

01.02.2018 23:12 · df9ts_user
english, review

From:
https://www.amateurfunk-sulingen.de/wiki/ - **Afu - Wiki des DARC OV Sulingen I40**

Permanent link:
**https://www.amateurfunk-sulingen.de/wiki/doku.php?id=fr:uhsdr_dev:uhsdrbuild**

Last update: **09.02.2018 08:15**